

PIONEER SVM1000



Produttore : Pioneer DJ

Cod.Art. : 6247

MIXER AUDIO - VIDEO 4 CANALI PER DJ

Progettato per essere utilizzato con i deck CD/DVD DVJ-1000, l'SVM-1000 consente ai DJ un controllo completo, sincronizzando gli elementi audio e video dei set. Grazie alla funzione "Visualiser capability" dell'SVM-1000, anche i DJ che lavorano soltanto con materiale audio potranno facilmente aggiungere elementi visivi sincronizzati con la musica. Completo di schermo LCD touch-screen, di una sorprendente gamma di effetti e di una qualità audio a 96 kHz/24 bit, l'SVM-1000 è MIDI assegnabile e funziona in modo analogo all'acclamata serie DJM Pioneer - che per i DJ significa porte aperte alla più totale libertà audiovisiva!

Visualizza video dimostrativi

Caratteristiche

- Canali 4
- Audio
- Terminali d'ingresso: DVD/LINE x 6 (RCA) - PHONO x 2 (RCA) - DIGITAL IN x 2 (COAXIAL) - MIC x 2 (XLR & 1/4-inch, can also be used as PHONE x 1, 1/4-inch PHONE x 1)
- Terminali d'uscita: MASTER OUT x 2 (RCA x 1, XLR x 1) - BOOTH

OUT x 1 (1/4-inch PHONE) - HEADPHONE MONITOR OUT x 1 (TOP PANEL

1/4-inch PHONE x 1) - REC OUT x 1 (RCA) - DIGITAL OUT x 1 (COAXIAL)

- Altri terminali: MIDI OUT x 2 (5P DIN x 1, USB x 1) - CONTROL (φ 3.5 MINI JACK) x 4
- Campionatura: 96 kHz
- Convertitore A/D, D/A: 24-bit
- Risposta in frequenza: 20 Hz - 20 kHz
- Distorsione armonica totale: 0.005% or less
- Rapporto segnale/rumore: 105 dB (LINE)
- Head Room. 19 dB

PIONEER SVM1000

- Video
- Terminali d'ingresso: DVD/VIDEO x 10 (COMPOSITE RCA) - S-VIDEO x 4 (S1/S2) -
- Terminali d'uscita: MASTER OUT x 4 - (COMPOSITE RCA x 1, COMPOSITE BNC x 1, COMPONENT BNC x 1, S1/S2 x 1) - MONITOR OUT x 2 (COMPOSITE RCA x 1, S1/S2 x 1)
- Altri terminali: VIDEO SYNC OUT x 4 (BNC)
- Altri terminali: USB , SD
- Alimentazione AC 220-240V (50/60 Hz)
- Consumo 58W
- Dimensioni senza imballaggio 500 mm (W) x 412 mm (D) x 202mm

(H)

- Peso 12.8 kg

Prezzo : €6.449,00 IVA inclusa (€5.286,07 esclusa IVA)
