

## WHARFEDALE PRO R2004FX



Produttore : Wharfedale Pro

Cod.Art. : 10190

### MIXER PASSIVO CON EFFETTI

L' R2004FX offre 8 ingressi mic / line mono, bilanciati con equalizzazione a 3 bande e un controllo semi-parametrico dei medi, più un equalizzazione a 3 bande su ognuno dei quattro canali di input stereo. L' R2004FX prevede anche 8 prese insert TRS da ¼ " nei canali mono, che permettono il collegamento di dispositivi esterni di elaborazione del segnale.

### Caratteristiche principali

- 8 ingressi mono
- 8 ingressi mic
- 4 ingressi stereo con tripla banda di equalizzazione
- 2 uscite master
- 2 uscite alt
- 1 uscita monitor
- 1 uscita cuffia
- 1 uscita rec
- 2 mandate ausiliarie
- Alimentazione phantom a 48V
- Dsp interno con 15 effetti digitali
- kit per il montaggio a rack 19" in dotazione

### Specifiche tecniche

- HUM AND NOISE: -127dB Equivalent Input Noise
- (Average, Rs=150): -95dB Residual Noise (MIX L / R, ALT 3~4, AUX SEND 1~2, CTRL ROOM) Master Fader at Nominal level and all
- Channel Assign Switch OFF
- Dimensions (HxWxD): mm 81.6x418.8x399.7 mm
- Weight: 7.5kg - 16.5 lbs

## WHARFEDALE PRO R2004FX

- MAXIMUM OUTPUT LEVEL: +22dB(MIX L / R,ALT 3~4) @600 ohm

(0.5% T.H.D at 1kHz):

- +22dB(AUX SEND1~2) @600 ohm
- +22dB(INSERT) @40k ohm
- +22dB(CTRL ROOM) @600 ohm
- Over 130mW (Headphone) @40 ohm

MASTER EQ:

- HI EQ (+ / -15dB) 12kHz Shelving
- MID EQ (+ / -15dB) 100Hz~8kHz (EQ for Frequency Variable) Peaking

- LOW EQ (+ / - 15dB) 80Hz Shelving

- POWER CONSUMPTION AC 100V / 120V / 230V / 240V ,50~60Hz

- TOTAL HARMONIC DISTORTION (THD): 0.0025% @+14dB 20Hz~20kHz,

(MIX L / R,ALT 3~4,AUX,EFX,CTRL ROOM) @600 ohm

MAXIMUM LEVELS:

- Mic in: +4dBu
- Tape in: +13dBu
- All other inputs: +25dBu

MAXIMUM VOLTAGE GAIN:

- 72dB MIC IN TO MIX L / R,ALT 3~4
- 72dB MIC IN TO AUX 1
- 72dB MIC IN TO AUX 2(POST),EFX
- 74dB MIC IN TO CONTROL ROOM L / R
- 72dB MIC IN TO REC L / R
- 54dB LINE IN TO MIX L / R,ALT 3~4
- 58dB LINE IN TO AUX 1
- 58dB LINE IN TO AUX 2(POST)
- 60dB LINE IN TO CONTRAL ROOM L / R
- 22dB ST IN TO MIX L / R,ALT 3~4
- 20dB AUX RETURN L / R IN TO MIX L / R
- 16dB TAPE IN TO MIX L / R

INTERFERENCE (CROSSTALK) at 1kHz:

- Main Fader Down: -85dBu Channel Alt / Mute Switch Engaged -80dBu
- Channel Fader Down: -70dBu
- MONO INPUT CHANNEL GAIN: 50dB variable (-60dB~-10dB), (-40dB~+10dB)

## WHARFEDALE PRO R2004FX

- PEAK INDICATOR Input Channel: Turns on 3dB Under Pre-fader Signal Clip
- LEVEL METERS 10-Segment LED x2 (Output of +4dB at 0dB) Main L / R
- PHANTOM POWER 48VDC
- EFFECTS PRESET: (1) Delay 1 (2) Delay 2 (3) Room 1 (4) Room 2 (5) Room 3 (6) Hall 1 (7) Hall 2 (8) Chorus 1 (9) Chorus 2 (10) Chorus 3 (11) Plate Reverb 1 (12) Plate Reverb 2 (13) Plate Reverb 3 (14) Rotary speaker (15) Flange (16) Bypass

Prezzo : €349,00 IVA inclusa (~~€286,07 esclusa IVA~~)

Prezzo in offerta : €259,00 IVA inclusa (€212,30 esclusa IVA)