

DIGIDESIGN Digi 003 Rack



Produttore : Digidesign

Cod.Art. : 5058

INTERFACCIA AUDIO FIREWIRE

Grazie alla sua vastissima gamma di opzioni I/O audio e MIDI, risoluzione audio ad alta definizione, la creatività e la velocità peculiari del software Pro Tools® - standard di riferimento del settore - la connessione FireWire nonché il vasto ed incredibilmente completo pacchetto di potente software allegato gratis, il nuovo 003™ Rack vi permette di ottenere, all'interno del vostro personal o project studio, una produzione audio con gli stessi alti livelli qualitativi di una struttura commerciale. Approfittate del suo gran numero di opzioni I/O per il collegamento ed il monitoraggio di tutta la strumentazione del vostro studio. Il suo design incredibilmente efficace, inoltre, vi permetterà un'ottimizzazione degli spazi anche all'interno di studi pieni zeppi di strumentazione e vi fornirà tutta la libertà di poter portare un sistema Pro Tools professionale ovunque ci sia bisogno della vostra perizia e creatività o dove vi porta l'ispirazione. Inoltre, con più di 60 potenti plug-in, strumenti virtuali, applicazioni compatibili e servizi di promozione artistica inclusi, gli operatori potranno disporre di tutto ciò di cui hanno bisogno (e anche di più) per la composizione, la registrazione, l'editing, il mixaggio e il mastering di audio per progetti musicali e di post produzione a computer. Con risultati professionali garantiti

Caratteristiche

- Mic Input
- Connector: Four balanced XLR jacks
- Mic Phantom Power: 48V
- Equivalent Input Noise: -129 dBu
- Frequency Response: +/- 0.1 dB, 20 Hz - 20 kHz
- Dynamic Range: 105 dB / 107 dB A-weighted
- THD + N: 0.0007% (-103 dB)
- Mic EIN: -129 dBu
- Input Sensitivity: +2.2 dBu
- Input Impedance: 2K Ohm

DIGIDESIGN Digi 003 Rack

- Line Input
- Connector: Four balanced 1/4" jacks
- Frequency Response: +/- 0.1 dB, 20 Hz - 20 kHz
- Dynamic Range: 111 dB / 113 dB A-weighted
- THD + N: 0.0007% (-103 dB)
- Input Sensitivity: +17.38 dBu
- Input Impedance: 22K Ohm
- DI Input
- Connector: Four unbalanced 1/4" jacks
- Frequency Response: +/- 0.1 dB, 20 Hz - 20 kHz
- Dynamic Range: 104 dB / 106 dB A-weighted
- THD + N: 0.0008% (-102 dB) - Balanced input
- Input Sensitivity: +17.16 dBu
- Input Impedance: >300K Ohm
- Aux Input
- Connector: Two balanced 1/4" jacks
- Frequency Response: +/- 0.1 dB, 20 Hz - 20 kHz
- Dynamic Range: 111 dB / 113 dB A-weighted
- THD + N: 0.00055% (-105 dB)
- Input Sensitivity: +17.16 dBu
- Input Impedance: 10K Ohm
- Line Output
- Connector: Eight impedance balanced 1/4" jacks
- Frequency Response: +/- 0.5 dB, 20 Hz - 20 kHz
- Dynamic Range: 110 dB / 113 dB A-weighted
- THD + N: 0.0007% (-103 dB)
- Output Sensitivity: +18 dBu
- Monitor Output
- Connector: Two impedance balanced 1/4" jacks
- Frequency Response: +/- 0.5 dB, 20 Hz - 20 kHz
- Dynamic Range: 110 dB / 112 dB A-weighted
- THD + N: 0.0008% (-102 dB)
- Output Sensitivity: +18 dBu
- Headphone Output
- Connector: Two unbalanced 1/4" jacks
- Frequency Response: +/- 0.5 dB, 20 Hz - 20 kHz
- THD + N: 0.0009% (-101 dB)
- Dynamic Range: 110 dB / 112 dB A-weighted
- Output Sensitivity: +23 dBu
- Digital Specification

DIGIDESIGN Digi 003 Rack

- Supported Sample Rates: 44.1, 48, 88.2, 96 kHz
- Maximum Word Length: 24-bit
- S/PDIF: 2-channel optical or RCA jack pair
- Digital Optical: TOSLINK (ADAT, max 48 kHz sample rate)
- Word Clock: Two BNC jacks
- Host Connection: Two IEEE-1394a (FireWire) ports
(6-pin-to-6-pin FireWire cable included)
- MIDI: 5-pin MIDI DIN connectors - one input, two outputs

Prezzo : €1.099,00 IVA inclusa (€900,82 esclusa IVA)
