

## MARKBASS R500



Cod.Art. : 5404

### TESTATA VALVOLARE PER BASSO 500W RMS

Rock means different things to different bass players, so with the R500, you can rock out old-school, rock hard, make your own alternative, or shred up the stage and steal the spotlight from your guitarists! This analog 500W amp (at 4 ohms; 300W @ 8 ohms) features a tube preamp that will break up just like you want it to, and a newly designed limiter that produces glorious distortion instead of cramping your style. The simple four-band EQ gives you all you need to access a wide range of different rock sounds. Gain controls the amount of tube overdrive, master controls your volume.

### Caratteristiche

- INPUTS
- INPUT impedance 500 Kohm, max. voltage 9 Vpp
- EFFECT RETURN impedance 33 Kohm, max. voltage 12 Vpp
- CONTROLS
- GAIN -80 dB to +25 dB range
- MASTER VOLUME
- GROUND LIFT switch on rear panel
- EQUALIZATION
- LOW center frequency: 80 Hz; level: ±12 dB
- LOW MID center frequency: 400 Hz, level: ±12 dB
- HIGH MID center frequency: 800 Hz, level: ±12 dB
- HIGH 3 kHz shelf, level: ±12 dB
- OUTPUT
- LINE OUT balanced XLR, max. voltage 25 Vpp
- EFFECT SEND unbalanced, max. voltage 12 Vpp (pre-EQ)
- TUNER OUT unbalanced, max. voltage 2 Vpp
- SPEAKER OUT speakon / 1/4" (x2)
- OTHER

Amplificatori per Basso > Testate per Basso

## MARKBASS R500

- WEIGHT 8.16 lbs / 3,7 kg
- DEPTH 11.89 in. / 30.2 cm
- HEIGHT 3.39 in. / 8.6 cm (2 rack units)
- WIDTH 14.5" / 36.8 cm (with rack ears: 19" / 48.3 cm)
- OPTIONAL FOOTSWITCH mute
- OUTPUT POWER 500W RMS @ 4 ohms, 300W RMS @ 8 ohms
- POWER REQUIREMENT 100V; 120V; 230V; 240V 50/60Hz

Prezzo : €819,00 IVA inclusa (~~€671,31 esclusa IVA~~)

Prezzo in offerta : €645,00 IVA inclusa (€528,69 esclusa IVA)