

WHARFEDALE PRO R1604FX



Produttore : Wharfedale Pro
Cod.Art. : 10189

MIXER PASSIVO CON EFFETTI

Il R1604FX offre 4 ingressi mic/line mono, bilanciati e quattro canali di ingresso stereo con 3 bande di equalizzazione su ogni canale.

Caratteristiche principali

- 4 ingressi mono
- 4 ingressi mic
- 4 ingressi stereo con tripla banda di equalizzazione
- 2 uscite master
- 2 uscite alt
- 1 uscita monitor
- 1 uscita cuffia
- 1 uscita rec
- 2 mandate ausiliarie
- Alimentazione phantom a 48v
- DSP interno con 15 effetti digitali
- kit per il montaggio a rack 19" in dotazione

Specifiche tecniche

- HUM AND NOISE: -127dB Equivalent Input Noise
- (Average, Rs=150): -95dB Residual Noise (MIX L / R, ALT 3~4, AUX, EFX, CTRL ROOM) Master Fader at Nominal level and all Channel Assign Switch off
- DIMENSIONS (HxWxD): 81.6 x 309 x 346 mm - 3.2 x 12.1 x 13.6 inches
- WEIGHT: 6kg - 13.2lbs
- MAXIMUM OUTPUT LEVEL: +22dB(MIX L / R, ALT 3~4) @600 ohm
- (0.5% T.H.D at 1kHz):

WHARFEDALE PRO R1604FX

- +22dB(AUX,EFX SEND) @600 ohm
- +22dB(INSERT) @40k ohm
- +22dB(CTRL ROOM) @600 ohm
- Over 130mW (Headphone) @40 ohm
- MASTER EQ:
- HI EQ (+ / -15dB) 12kHz Shelving
- MID EQ (+ / -15dB) 2.5kHz Shelving
- LOW EQ (+ / - 15dB) 80Hz Shelving
- TOTAL HARMONIC DISTORTION (THD): 0.0025% @+14dB
20Hz~20kHz
(MIX L / R,ALT 3~4,AUX,EFX,CTRL ROOM) @600 ohm
- MAXIMUM LEVELS:
- Mic in: +4dBu
- Tape in: +13dBu
- All other inputs: +25dBu
- MAXIMUM VOLTAGE GAIN:
- 72dB MIC IN TO MIX L / R,ALT 3~4
- 72dB MIC IN TO AUX 1
- 72dB MIC IN TO AUX 2(POST),EFX
- 74dB MIC IN TO CONTROL ROOM L / R
- 72dB MIC IN TO REC L / R
- 54dB LINE IN TO MIX L / R,ALT 3~4
- 58dB LINE IN TO AUX 1
- 58dB LINE IN TO AUX 2(POST)
- 60dB LINE IN TO CONTRAL ROOM L / R
- 22dB ST IN TO MIX L / R,ALT 3~4
- 20dB AUX RETURN L / R IN TO MIX L / R
- 16dB TAPE IN TO MIX L / R
- INTERFERENCE (CROSSTALK) at 1kHz:
- Main Fader Down: -85dBu
- Channel Alt / Mute Switch Engaged: -80dBu
- Channel Fader Down: -70dBu
- MONO INPUT CHANNEL GAIN: 50dB variable (-60dB~-10dB),
(-40dB~+10dB)
- PEAK INDICATOR: Input Channel Turns on 3dB Under Pre-fader
Signal Clip
- LEVEL METERS: 10-Segment LED x2 (Output of +4dB at 0dB)
- Main
- L / R
- PHANTOM POWER: 48V

Mixer > Mixer Passivi

WHARFEDALE PRO R1604FX

- EFFECTS PRESET: (1) Delay 1 (2) Delay 2 (3) Room 1 (4) Room 2 (5) Room 3 (6) Hall 1 (7) Hall 2 (8)Chorus 1 (9)Chorus 2 (10) Chorus 3 (11) Plate Reverb 1 (12) Plate Reverb 2 (13) Plate Reverb 3 (14)Rotary speaker (15)Flange (16) Bypass

Prezzo : €269,00 IVA inclusa (~~€220,49 esclusa IVA~~)

Prezzo in offerta : €199,00 IVA inclusa (€163,11 esclusa IVA)