

FOCUSRITE VRM Box



Focusrite®

Cod.Art. : 10680

INTERFACCIA AUDIO USB PER MIXARE IN CUFFIA

VRM BOX (Virtual Reference Monitoring) supera l'ostacolo maggiore per il mixaggio con cuffie facendo sì che sembri di ascoltare il tuo mix attraverso degli altoparlanti. Infatti, i livelli di rumore attraverso gli altoparlanti può rendere impossibile per la maggior parte di mixare in casa, soprattutto a tarda notte. Con VRM, si può mixare in qualsiasi momento e ovunque. Utilizzando una qualsiasi coppia di cuffie da monitoraggio VRM permette di scegliere il proprio ambiente di mixaggio da un soggiorno, una camera da letto o uno studio professionale.

Specifiche tecniche

HEADPHONE OUTPUTS (OUTPUTS 1-2)

- Output impedance: < 10 Ω;
- Power output into 150 Ω: 15mW
- Power output into 50 Ω: 30mW
- THD+N: -100dB (0.001%) (-1dBFS input, 20Hz/22kHz bandpass filter, 150 Ω load)
- Signal to Noise Ratio: > 105dB

S/PDIF DIGITAL INPUT

- Automatic Sample Rate conversion
- Supported sample rates: continuous from 32kHz to 192kHz
- THD+N: < -110dB any sample rate

CROSSTALK (CHANNEL ISOLATION)

- Any output to output: > 100dB

DIGITAL PERFORMANCE

- D/A Dynamic Range: 120dB (A-weighted)
- Measured D/A Dynamic Range: 108dB (A-weighted)

FOCUSRITE VRM Box

- Clock Source: Internal Clock only Clock jitter < 250 picoseconds
- Supported Sample Rates: 44.1kHz & 48kHz
- Input channels to computer: S/PDIF (stereo)
- Output channels from computer: Headphones (stereo)

CONNECTORS AND CONTROLS

- Stereo S/PDIF input on RCA
- Stereo Headphone Output on 1/4" TRS
- Headphone Output Level control (analogue)
- 4-pin USB2.0 compatible socket

DIMENSIONI E PESO

- NetWeight: 123g
- Unboxed: 68mm x 25mm x 68mm (W x H x D)

Requisiti minimi di sistema

- Windows: XP (service pack 3), Vista, 7 (32 and 64-bit)
- Mac: OS X 10.5 Leopard (Intel only), OS X 10.6 Snow Leopard

Prezzo : €98,00 IVA inclusa (~~€80,33 esclusa IVA~~)

Prezzo in offerta : €77,00 IVA inclusa (€63,11 esclusa IVA)