

## AMERICAN DJ Pixie Driver 8000 V2

No image



Cod.Art. : 202331

ZCL

Pixie Driver 8000 V2 is designed specifically for the ADJ Pixie Strip 30, Pixie Strip 60, and Pixie Strip 120. It provides easy and versatile control options including simple on-board manual dimming and strobe control, plus full pixel mapping control of 8,160 max pixels via Kling-Net, Art-Net or sACN (streaming ACN) protocols.

The Pixie Driver 8000 V2 features a universal auto switching power supply (100-240V), a 4-button LCD control menu display, RJ45

Ethernet in/out ports, (8) Pixie Strip outputs which use proprietary, 4-pin combo cables (sold separately) that supply power and data to each pixie strip (available in lengths from 2 to 50 feet (For additional details, see Accessories Sold Separately under the Specifications section). The Pixie Driver 8000 can be mounted in a standard 19-inch rack (rack ears included) or attached to truss with a clamp (not included).

Caratteristiche

Specifications

Control Features:

Power / data supply for ADJ Pixie Strip 30, Pixie Strip 60, and Pixie Strip 120

Manual RGB mode

Internal programs

Manual Dimming and Strobe Control

Full Pixel Mapping Control

Drives up to 8,160 Pixels via KlingNet, ArtNet and sACN (1,020 Pixels per port)

OLED screen with 4-button menu

USB port for Firmware Updates

Control Quantity:

## AMERICAN DJ Pixie Driver 8000 V2

KlingNet / Art-Net / sACN: (34) Pixie Strip 30's, (17) Pixie Strip 60's or (8) Pixie Strip 120's (Per port. Or any combination not exceeding 1,020 pixel per port)

Connections:

Power: PowerLock Input

Two KlingNet / Artnet ethernet ports

Eight 4-pin DC24V power/data outputs to Pixie Strips

Mounting Options:

Bolt to add a clamp to hang from truss (clamp and truss not included)

Includes 19-inch rack mount ears

Safety eye

Electrical:

Multi-voltage operation: AC 100-240V, 50/60Hz

Power Consumption: 1,600W max

-4°F to 113°F (-20°C to 45°C)

Dimensions / Weight:

Dimensions (LxWxH): 11.6" x 18.9" x 4.8" / 294x480x120mm

Weight: 13.4 lbs. / 6.1 kg.

Included Accessories:

(1) PIXEL BC10 (PIX339): 10', 4-pin cable. Connects between Pixie Driver 8000 V2 and Pixie Strip.

(1) SIP20MPC (SIP293): Power Input cable

(2) 19" Rack Ears

Accessories Sold Separately:

PSLC1 (PIX158): 1-foot Pixie Strip to Pixie Strip or Pixie Driver to Pixie Strip Link Cable

PSLC3 (PIX174): 3-foot Pixie Strip to Pixie Strip or Pixie Driver to Pixie Strip Link Cable

PSLC5 (PIX188): 5-foot Pixie Strip to Pixie Strip or Pixie Driver to Pixie Strip Link Cable

PSLC10 (PIX200): 10-foot Pixie Strip to Pixie Strip or Pixie Driver to Pixie Strip Link Cable

PSLC15 (PIX213): 15-foot Pixie Strip to Pixie Strip or Pixie Driver to Pixie Strip Link Cable

PSLC25 (PIX229): 25-foot Pixie Strip to Pixie Strip or Pixie Driver to Pixie Strip Link Cable

PSLC50 (PIX242): 50-foot Pixie Strip to Pixie Strip or Pixie Driver to Pixie Strip Link Cable

Specifications subject to change without notice.

---

## AMERICAN DJ Pixie Driver 8000 V2

Prezzo : €1.580,00 IVA inclusa (€1.295,08 esclusa IVA)

---

strumentiMusicali.net