

STANTON M212



stanton

Cod.Art. : 8510

MIXER PER DJ 2 CANALI

Newly optimized and DJ friendly, the M.212 is a durable but stylish 2-Channel mixer built for everyday performance.

Caratteristiche

INPUT / OUTPUT IMPEDANCE & SENSITIVITY

- Line: -14dB/10K OHM \pm 2dB
- Phono: -50dB /47K OHM \pm 2dB
- Mic: -60dB /2.2K OHM \pm 2dB
- Master: 1K OHM
- Phones: 0dB/33 OHM \pm 2dB (LOAD=32 OHM)
- MAX. OUTPUT (THD=1%) Master: MORE THAN +14dBV (8.0V)
- CHANNEL BALANCE WITHIN 3dB
- FREQUENCY RESPONSE: (line) 20-20KHz \pm 2dB
- OUTPUT NOISE (IEC-A WEIGHTED) (line to MST): LESS THAN -90dBV
- THD + N: (MASTER 0dBV OUTPUT, MAXIMUM GAIN, w/ 20kHz LPF) (line) LESS THAN 0.05% 20 - 20KHz
- Signal to Noise Ratio \geq 106dB
- Crosstalk LESS THAN -80dB AT 1KHz BETWEEN CHANNELS. (TERMINATED UNUSED INPUTS)
- Mic EQ: \pm 10 +/- 2dB AT 10KHz
- Hi: \pm 10 +/- 2dB AT 100Hz
- Low: \pm 10 +/- 2dB AT 100Hz
- Channel EQ:
 - Hi 9 +/- 2dB AT 13KHz -15 +/- 3dB AT 13KHz
 - Mid 9 +/- 2dB AT 1KHz LESS THAN -23dB AT 1KHz
 - Low 9 +/- 2dB AT 70Hz -26 +/- 3dB AT 70Hz

Prodotti per DJ > Mixer per DJ

STANTON M212

- Line Inputs: 2 (RCA), -10dB/47K ohm
- Phono Inputs: 2 (RCA), -50dB/47K ohm
- DJ Mic Input: 1 (1/4"), -50dB/6K ohm
- Master Output: 1 (RCA), -10dB/47K ohm
- Headphone Output: 1 (1/4"), -3dB/33 ohms
- Mic Tone: +/-10dB (Hi, Low)
- Dimensions (LxWxD): 230 (W) X 267 (D) X 111 (H) mm
- Weight: 1.61Kgs (3.5 lbs.)

Prezzo : €129,00 IVA inclusa ~~(€105,74 esclusa IVA)~~

Prezzo in offerta : €95,00 IVA inclusa (€77,87 esclusa IVA)