

MARKBASS AH 250 Acoustic



Cod.Art. : 9092

TESTATA 250W PER STRUMENTI ACUSTICI

La Markacoustic AH 250 è una testata compatta e leggera per strumenti acustici. Collegala al tuo cabinet preferito oppure usala come preamp senza necessariamente dover collegare uno speaker prelevando il segnale dall'uscita Line Out XLR e tenendo il volume master a zero. L'AH 250 ha una potenza di 150W @ 8 ohms o 250W @ 4 ohms, e offre due canali preamp (un jack da ¼" e un combo jack XLR/1/4" con 48V phantom power switchabile). I controlli anti-feedback e phase reverse ti consentono di catturare la vera essenza del tuo suono acustico anche a volumi elevati.

Specifiche tecniche

Inputs:

- Channel 1: Impedance 500 kohm, max. Voltage 10 vpp
- Channel 2: Impedance 500 kohm, max. Voltage 10 vpp
- Balanced channel 2: Impedance 500 kohm, max. Voltage 20 vpp
- Insert point: Impedance 10 kohm, max. Voltage 20 vpp

Controls ch 1:

- Gain: -45 db to +28 db range
- Effect mix: internal effect only
- Eq low: 40 hz, cut or boost up to 16 db
- Eq mid: 600 hz, cut or boost up to 16 db
- Eq high: 6 khz, cut or boost up to 16 db

Controls ch 2:

- Gain: -43 db to +26 db range
- Phantom power: 48v dc

Effect mix:

MARKBASS AH 250 Acoustic

- Internal effect only
- Vpf (variable pre-shape filter)
- Center frequency: 380 hz (cut)
- Eq low: 40 hz, cut or boost up to 16 db
- Eq high: 6 khz, cut or boost up to 16 db
- Other controls:
- Phase: 0°, 180°
- Antifeedback: 20hz (off), 400 hz

Output:

- Insert point: unbalanced, max. Voltage 25 vpp
- Send mix: balanced, max. Voltage 20 vpp

Other:

- Width: 10.87 in. / 27.6 cm
- Depth: 10in. / 25.6 cm
- Height: 2.8 in. / 7.1 cm
- Weight: 6.39 lbs / 2.9 kg
- Output power: 250w rms @ 4 ohm, 150w rms @ 8 ohm
- Power requirement: 100/120v; 230v; 240v 50/60hz (voltage is factory preset according to region of sale)

Prezzo : €599,00 IVA inclusa (~~€490,98 esclusa IVA~~)

Prezzo in offerta : €479,00 IVA inclusa (€392,62 esclusa IVA)